



Maxi

WORK & SAFETY



P-LIGHT Maxi

Compact, easy-fit battery backup with robust, fully welded design.

Maxi is designed mainly for operating 2-circuit parking and position lights on trailers during short-term parking, e.g. when arranging goods and when additional functions are required, such as switching on strobes, cabinet lighting, work lighting, radio control, etc.

When the truck is uncoupled, **Maxi** powers electrical equipment so as to maintain a safe work situation and to allow goods to be handled carefully in the cabinet, for examples. At the same time, other road users can see the rig in plenty of time when it is illuminated.

When the truck is coupled back up, battery charging starts automatically via the **lights** and the integrated charger makes sure that the batteries always receive a **100 %** correct charge while in motion, summer and winter.

All P-LIGHT devices have:

A revolutionary **New** charger with diagnostic program and monitoring of automatic fuses, batteries, charge, etc.

Programmable light operation (AUTO On/Off).

Batteries with rubber suspension to prevent vibration damage.

Battery gard to prevent deep battery discharge.

Technical info

Material:	Electropolished 3 mm stainless steel
Width:	430 mm (490 inc. bracket)
Height:	230 mm (260 inc. bracket)
Depth:	250 mm
Weight:	≈ 45 kg inc. batteries
Installation:	On frame or toolbox
Battery:	24 VDC / 40 Ah (Maintenance-free)
Charging:	< 10 A (≈ 240 W) while driving (Connection min 2 x 2.5 mm ² leads)
Outputs:	2 x 100 W (Parking lights) 1 x 200 W (e.g. Cabinet lights) 1 x 200 W (AUX, e.g. Radio control)
Operating-times:	(Fully charged batteries + 20° C) 20 W ≈ 48 h 50 W ≈ 19 h 100 W ≈ 9 h 200 W ≈ 4 h

The Force is with You!



Manufacturer & Sellers
InnoNet AB - SE-342 50 Vislanda - Sweden
Phone +46 472 483 83 Info@innonet.se

www.p-light.com



P-LIGHT is registered trade mark owned by InnoNet AB